



# PR-1240

## 1-CHANNEL 100V POWER AMPLIFIER

This power amplifier was designed for general commercial and industrial use. 1 x 240W output capacity, adjustable by means of a knob on the front. It can also be used, for example, to expand a four-channel amplifier to 5 or 6 channels.



A bar or pub is just what we need to get us into the right mood! Why not add a bit of extra power to help things along?

output capacity 100V	1 x 240W
output capacity RMS 8Ω	monitor
frequency range	50Hz - 16kHz
zones	1
direct output	70V / 100V / 4 - 16Ω
LED level indicator	yes
output (link)	XLR / jack
amp in	XLR / jack
safety	over-voltage and power surges
cooling	automatic ventilator / thermal sensor
power supply	240V AC
power consumption	400W
dimensions (h x w x d)	88 x 484 x 358mm - 2 RS
weight	13.2kg

