

# METEOR 0.5

Top of the Range Wireless Subwoofer



The METEOR 0.5 is an essential component, whether assembling a high-performance 2.1 channel audio system or upgrading your home cinema.

- **Subwoofer with TRIANGLE's well known sound, speed and dynamics** for pure audio and home cinema use.
- **300W class AB amplifier** for optimal sound quality (low distortion and impressive dynamics).
- **New 28cm loudspeaker driver** with sandwich diaphragm, fibreglass and paper honeycomb core, with a 150mm magnet assembly.
- **Subwoofer equipped with a bass reflex system** for deeper bass reproduction.
- **It is discrete**; it is cube-shaped in order to make it easier to fit into a living room. It can be hidden behind an armchair or a piece of furniture. Its two smooth, flat sides make it easy to install against a wall.
- It has a **piano black finish** and thus blends in with all types of speakers and flat screens, and can be installed in a room dedicated to home cinema.
- **Wireless connection**. Easy to connect, requires only AC cord. Thus it is possible to set up a sound system in a place other than the normal listening room. It is the first time a European manufacturer has offered this with a subwoofer.
- **LED on front panel** to indicate power-on and stand-by (three colours, orange for wireless transmission, red for stand-by, green for wired transmission).



# METEOR 0.5

CODE EAN : 3660216002884



## TECHNICAL DESCRIPTION

Type	Active bass reflex subwoofer with bottom firing port
Number of drivers	1
Diameter (cm / in)	28 / 11
Bandwidth (+/-3dB Hz)	28 - 160
Amplifier power (W Rms)	300
Remote control / wireless connection	yes / yes
Dimensions (H x W x D mm / in)	430 x 380 x 423 / 17 x 15 x 16.6
Weight (Kg) / (lbs)	21 / 46.5
Connections	<ul style="list-style-type: none"> <li>• 1 RCA stereo input,</li> <li>• 1 high-level loudspeaker terminal connection</li> <li>• 1 RCA LFE</li> </ul>
Functions	<ul style="list-style-type: none"> <li>• In « Auto » mode, light comes on when signal is detected</li> <li>• Goes off automatically after 15 minutes without signal</li> <li>• Phase inversion variable between 0 and 180°</li> <li>• Volume control</li> <li>• Remote control in credit card style (ditto METEOR 0.1 Tc)</li> <li>• 110V / 220V switch</li> </ul>