

## Pro-Ject Stereo Box

Integrated amplifier with remote control



### Good sound from sound technology

- Metal case shields the electronics from vibrational and electromagnetic interference
- Bi-Phase PWM-circuit (Pulse Width Modulation)
- Gold plated RCA connection sockets
- Outboard power supply included

### Features

- Remote controllable
- Small size allows easy placement
- Optional input expander Pro-Ject Switch Box providing four additional inputs. Automatic synchronization with the input selector of the Pro-Ject Stereo Box.
- Pro-Ject Audio digital amplifiers achieve 80% energy efficiency

### Technical specifications

Power output:	2 x 20W/30W at 8ohms/4ohms (both channels driven)
Frequency response:	20Hz - 20kHz (+ - 0,2 dB)
Channel separation:	> 40dB at 20kHz
Noise floor:	> -100dB (A weighted)
THD:	< 0,05% at 10W
Gain:	22dB
Line-level inputs:	2 pairs RCA/Phono sockets
Input impedance:	20kohms
Outboard power supply:	20V/3A DC (peak 7A DC), suitable for your country's mains supply
Power consumption:	20V/3A DC
Dimensions (W x H x D):	103 x 38 x 141 mm
Weight:	720g without power supply

The manufacturer reserves the right to alter the technical specifications without notice.



Available in silver or black finish